



Visit product page



I MIX 4

L005644

Compact, portable mixing console, 2mono + 2 stereo input, 1bus, USB interface

TECHNICAL DETAILS

Features

- 4-way mini mixing console.
- 2/4mic/line input, 48V phantom power, be used for condenser microphone.
- 2 way stereo line input.
- q; 3.5mm CD input(I MIX 1 A NO).
- 2 band EQ, +/- 15dB EQ at 80 Hz & 12KHz.
- Main output control (L/R).
- Headphone output control.
- RCA input/output.
- 1 way Subsidiary output(I MIX 1 NO).
- 4 band LED level indicator.
- Compact structure, which can be used in different locations.
- Convenient for operating.
- External supply power (100-265V 50/60Hz), which can be used in any country.
- USB recording / playing function.

Technical Specifications

- Frequency response: 20 Hz to 20 kHz.
- THD: <0,008 %.
- Residual noise: Main output - 103 dB, subsidiary output: -90 dB.
- Gain scope: Mic input -20 dB to + 45 dB, Line input -20 dB to +25 dB.

Phantom power: +48 V DC.

EQ: Hi ± 15 dB @ 12 kHz, Low ± 15 dB @ 80 Hz.

Max output: Main output + 21 dBu, headphones + 18 dBu.

Input impedance: Mic 2,3 k Ω bal, Line 20 k Ω bal, CD/RCA input 24 k Ω unbalanced.

Output impedance: Main 120, RCA 1k, Headphone 25.

Level indicators: (Clip), 0, -10, -20.

Supply power: AC 100/240 Volt, 50/60 Hz, DC 12V power supply.

Consumption: 11 Watt.

Dimensions: 220 x 210 x 68 mm.

Net weight: 0,98 Kg.

PHOTOS



PRODUCT VIDEO




ACCESSORIES



I MIX 4/2 Stand

Microphone stand adapter
for I MIX 4 and I MIX 6.



www.fos-lighting.eu

